



## MMATS Monster 12 dual 2 or 4 ohm

Theil/Small	Dual 4 ohm	Dual 2 ohm
Znom=	2.000 ê	1.000 ê
Sd=	0.0519 sqM	0.0519 sqM
Fi=	45.519 Hz	38.812 Hz
Revc=	1.990 ê	1.000 ê
Fo=	46.416 Hz	39.252 Hz
Krm=	0.284 mê	0.000 mê
Vas=	26.3199 Litr	21.0630 Litr
Qms=	3.357	4.391
Xmx=	11.5000 mM	10.0000 mM
Kxm=	53.012 mH	0.000 mH
Cms=	68.7040 uM/N	55.0665 uM/N
Qes=	0.817	0.529
Cmx=	11.5000 mM	10.0000 mM
Erm=	1.171	0.000
Mms=	171.1300 Gram	298.5610 Gram
Qts=	0.657	0.472
Exm=	0.551	0.000
Mmd=	164.3235 Gram	291.7625 Gram
Pmx=	1000.0 Wrms	1000.0Wrms
SPLo	86.97 dB	85.70 db



Model	Sealed (Net)	Vented (Net)	Port Specs	Port Disp	Woofers Disp
Monster 12	<u>N/A</u>	2.00 cu.ft	20 sq." X 18" Long	.12 cu.ft	.20 cu.ft.

Hole Cutout Diameter	11.187"
Overall Diameter	12 5/8
Mounting Depth	6"

**\*\* Enclosure Size is NET Interior Volume, EXCLUDING speaker and port displacement!!**

**3" round port equals 7.07 sq. inches**

**4" round port equals 12.56 sq. inches**

**6" round port equals 28.26 sq. inches**

